

Setting Up MMS & Internet for another Carrier

Process Overview

You will need to create two new APN's (Access Point names) one for Internet & the other for MMS to use this functionality. The default Telstra APN's pre-programmed in to the handset are; 'Telstra Internet' & 'Telstra MMS'. This procedure aims to outline how to create an APN, listing the associated fields to enter & how to set. The settings required will need to be obtained from your carrier.

To Create an 'Access Point':

1. From the '*idle*' screen **PRESS** 'OK' to access the main menu
2. **NAVIGATE** to '*Settings*' & **PRESS** 'OK' to explore
3. **NAVIGATE** to the '*Handset*' tab
4. **SCROLL** to '*Access point settings*' and **PRESS** 'OK' to Select
5. **PRESS** the top left '—' key to **view** '*Options*'
6. **CHOOSE** '1: *New*' and **PRESS** 'OK' to select
7. **ENTER** the following information in to the appropriate fields
 - Name
 - APN
 - Authenticate mode {if present}
 - Username
 - Password
8. **REPEAT** steps 1 to 8 to set up the two required APN's (1 x Internet, 1 x MMS)

To Set the MMS APN:

1. From the '*idle*' screen **PRESS** 'OK' to access the main menu
2. **NAVIGATE** to '*Messages*' & **PRESS** 'OK' to explore
3. **SCROLL** to '*Settings*' and **PRESS** 'OK' to Select
4. **PRESS** 'OK' to Select '*Mul. Msg. Settings*'
5. **SET** the following
 - Retrieval Settings
 - Delivery Mode
 - Time per page
 - Delivery report
 - Validity
 - Anonymous Msg.
 - APN
6. **ENTER** the following information
 - Server address
 - Proxy server address
 - Proxy server port

To Set the Internet APN:

1. From the '*idle*' screen **PRESS** 'OK' to access the main menu
2. **NAVIGATE** to '*Browser*' & **PRESS** 'OK' to explore
3. **PRESS** 'OK' to Select '*Connect Settings*'
4. **PRESS** the top left '—' key to **view** '*Options*'
5. **SCROLL** to '*Create*' and **PRESS** 'OK' to Select
6. **ENTER / SET** the following information
 - Name
 - Homepage
 - Proxy
 - Proxy address
 - Proxy port
 - APN

NOTE: This has not been tested, you may need to alter further settings to get this operational.